

MOTOR SPEED CONTROL

STOCK NO. 40112 (120V) 40113 (208-240V)

Kit includes:
40112-40113 Control
Installation Instructions
#10 x 3/8 self tapping screw
New Wiring Schematic
Retrofit sticker for Cover



WARNING: TO REDUCE THE RISK OF ELECTRIC SHOCK, FIRE & PERSONAL INJURY, INSTALLATION MUST BE PERFORMED BY QUALIFIED ELECTRICAL SERVICE PERSONNEL. DISCONNECT POWER TO THE DRYER BEFORE INSTALLING THE SPEED CONTROL. SPEED CONTROL TO BE INSTALLED ON XLERATOR DRYERS PRODUCED AFTER 1/1/2009 SERIAL # 370656 AND HIGHER.

TO BE USED ONLY FOR 120V AND 208-240V MODELS SHOWN BELOW:

XL - followed by W, C, GR, BW, BSP, SB, SPO, SS, SW, SC, SSP, SI or SP, followed by V or 8, and or H

1) Confirm power is turned off to the dryer, and remove the cover using the special wrench which was provided with the dryer.

2) Install the speed control onto the boss shown in (Fig. 1,2) using the self-tapping screw provided.

3) Find and disconnect the white heater wire from the (N) side of the terminal block. Connect the wire onto the tab labeled "3" on the speed control (Fig. 1).

4) Find and disconnect the white motor wire from the (N) side of the terminal block. Connect the wire onto the tab labeled "2" on the speed control (Fig. 1). If the wire does not reach, gently pull slack as needed from where the wire enters the motor housing.

5) Locate the pre-attached white wire connected to the tab labeled "1" and attach the other end to the (N) side of the terminal block (Fig. 1).

6) Locate the new wiring schematic sticker provided, and place directly over existing schematic in Fig. 1.

7) Install retrofit sticker provided, to the bottom, right side of cover opposite dryer model sticker in Fig. 3.

8) Check that all connections are secure and adjust motor speed as desired by turning the knob. Reattach the dryer cover. Restore power and check for proper function.

